

4G LTE INTERCOM SPECIFICATION

FEATURES AND BENEFITS



E1K

H 224 x W 96 x D 40 Number of Users : 1

'COMMTEL COMMAND ONE' APP

?

I.

* 0 • 4 40 4 1 10:4

Gate

OPEN

HOLD

n walking

CLOSE

na remotely

SETUP

DOWNLOAD THE

🕥 Commtel Command One

M 16

Door

OPEN

HOLD

OPEN

CLOSE

<

- Consider the consenuences

VIEW SAFETY MESSAGE

Do not

- 316 marine grade stainless steel faceplate
- 40mm low profile, high strength, anthracite grey alloy cast back box
- LED downlight
- Stainless steel security screws
- Surface mounted
- Downward facing microphone
- I THS Horwood quality sound
- Call up to 3 numbers from a single call point
- IP64 rated
- Time clock with 3 profiles
- 2 year warranty
- Backlit, vandal resistant keypad
- I Timed trade button and clear button
- 100 pin codes for coded entry

Please pay particular attention

to the Safety Message Contents

included on the App front page

(View Safety Message).

EASY TO USE

The single call button can ring through to up to 3 cascading landline or mobile phone numbers. Once answered, if the recipient wants to grant access to the visitor they simply press the # key on their phone.

DOWNLOADABLE ACTIVITY LOGS

Download the last 10,000 interactions with the unit and see who is gaining entry, how and when. A great security feature for free.

DIAL TO OPEN

• Authorise up to 100 numbers the ability to call the unit and open your door/gate. A modern and more cost effective alternative to traditional access control.

EASY TO INSTALL

TWO YEAR WARRANTY

TECHNICAL SPECIFICATION

- Power 12 Volt 1 Amp. DC PSU fitted with a 3A fuse (supplied and must be dedicated to the Telguard intercom unit). Power Consumption: 120 mA Idle @ 12 Volts.
- Telephone Type Standard DTMF (Dual Tone Multi Frequency) generating telephone, cordless or mobile phone.
- Programming Remotely programmable via App, SMS or via GSM modem. Locally via USB cable.
- Relays 3: 1 x 2A, 2 x 200mA, 2 x Auxiliary inputs.
- Relay Activation Time 1 60 seconds, adjustable locally and remotely.
- Operating Commands # Pulses RL1, 1# Pulses RL1, 2# Pulses RL2, 3# Latches RL3, 6# Unlatches RL3.
- Time Clocks This utilizes the on board time clock enabling custom profile functions to be activated.
- Authorised Call Access 100 telephone numbers can be stored. Calling the unit, from an authorised telephone number activates the relay.



OPEN | HOLD | CLOSE AT THE CLICK OF A BUTTON

www.commtel.tech/apps

0

EU CE Declaration of Conformity and Radio Equipment Directive is available at www.commtel-uk.com | GB-RH10 9XN

dhf



